

Wireless 2-Line LED Sign

Model: MWC-112



“Wireless Professionals with Years of Experience”

Visit Our Website at:

www.Multitonenewireless.com

P/N= MWC-112

No Relay Model

“Works Like a Pocket Pager”!

Also Available in 20-52 Characters - (Model: MWC-122)

Features:

- ♦ Alphanumeric LED Display
- ♦ Displays Exactly what your Pager Receives - No Special Formatting Required
- ♦ 1 or 2 Line Operational Mode (Specify when Ordering)
- ♦ 1-Line Mode: Displays 10-12 Characters, Scrolls from Right to Left for Longer Messages
- ♦ 2-Line Mode: Displays 22-24 Characters, Scrolls from Right to Left for Longer Messages
- ♦ Messages are Received Wirelessly from On-Site Paging System or from Wide Area Paging Service
- ♦ Messages are Automatically Manages for up to 24 Active Messages
- ♦ Message Time-Out Option using either Run-Time or Message Display Count as Time-Out Triggers
- ♦ Real-Time Clock with Message Stamping Option
- ♦ Priority Message Stacking for up to 5 Priority Messages
- ♦ Priority Message By Prefix (911)
- ♦ Message Clearing Feature using “Reset” by Prefix / Suffix
- ♦ Frequency, Cap Codes and Pager Baud Rate Programmed by way of PC Software.
- ♦ All Options and Features are Set by OTA Commands
- ♦ Program Software and Over-the-Air Commands (OTA) CD
- ♦ Delete All Messages by way of Over-the-Air Command
- ♦ Programmable Default Message (Up to 50 Characters)
- ♦ Wall Mount Bracket Kit Included
- ♦ Back to Back Signs Ceiling Hanging Kit Available
P/N= AS Brackets

Specifications:

- ♦ Model: MWC-112 Alpha Sign
- ♦ Case: Dark Aluminum with Red Display
- ♦ Frequency: 408-473 MHz, 138-174 MHz and 929-931 MHz
- ♦ RF Data Rate: 512 / 1200 / 2400bps for POCSAG, 1600 / 3200 / 6400bps for FLEX
- ♦ Channel Spacing: 25 KHz (WB) or 12.5KHZ (NB)
- ♦ Code Format: POCSAG or Flex
- ♦ Cap Codes: 6 Cap Codes (For POCSAG)
- ♦ LED Array: 160 x 16
- ♦ Characters: 10 / 4” Tall (One-Line) or 22 / 2” Tall (Two-Line)
- ♦ Dimensions: Case - 28” L x 6” H x 3” D
- ♦ Weight: Approx – 13 Lbs.
- ♦ Power: 110VAC (6Ft. Cord attached with 2 Prong Plug)

NOTE: Frequency Required when Ordered

Multitone Wireless (Canada)

1.877.902.9696

Sales@multitonenewireless.com